		TECHNICAL DATA SHEET : ELECTRONIC BALLAST					
F	Project : STANDARD Model No : HPY-240-114-IT5-OAF			Type : PROFESSIONAL Remark :			
<b>_</b>							
Model : 1 x 14W FTL BALLAST				Input Characteristics			
				1 Voltage (Un)		240 Vac	
				2 Ope	erating Voltage Range	140 ~ 277 Vac	
				3 Fre	quency (Hz)	50 / 60 Hz	
				4 Cur	rrent (A)	0.07 A	
				5 Wa	ttage (W)	17 W	
				6 Pov	wer Factor (PF)	0.98 (PPFC)	
c					rrent Harmonics (Athd)	< 10%	
				er Current Protection	Yes		
282.0				9 Surge Withstanding Capacity		Yes	
					er Voltage Application	@ 320Vac 48Hrs &	
				10 000	er voltage Application	@ 360Vac 2 Hrs	
Output Characteristics					Mechanical Details		
1	Lamp Types		F14-T5	1 Weight		145 gm	
2	Number of Lamps		1	2 Case Dimer	nsions		
3	Lamp Connection		Single	Le	ength W/Mount	282 mm	
4	Lamp Current		0.165A	Ce	enter to Center ( CTC )	272 mm	
5	Operating Frequency		<u>&gt;</u> 40 KHz	W	idth	24 mm	
6	gnition Method		RS	Height		21 mm	
Ballast Characteristics				3 Case Material		Metal Case	
1	Lamp Current Crest Factor (CCF)		<u>&lt;</u> 1.70	4 Wiring Diagram		On Screen	
2	Ballast Efficiency (BE)		<u>&gt;</u> 80%	5 Input / Outp		Connectors Push Type	
				6 Wires Length & Colors			
				Input ( White & Black )		N/A	
Protection Features				Output ( White )		N/A	
1 Deactivated Lamp			Yes	Output ( Gray )		N/A	
2	Restart or Latching	·		7 Potting		N/A	
2 Restart or Latching Latching 7 Potting N/A							
Environmental Operating Details Notes							
1	Minimum Lamp Starting Temp	• •	0°C	A High power factor Electronic ballast specially designed			
2	Max. Ambient Temperature		50°C	for heavy duty use . <u>Key features</u> :- • Slim Design			
3	Max. Case Temperature (Tc)		70°C				
				<ul> <li>High Voltage withstanding capacity.</li> <li>High Surge withstanding capacity</li> <li>Long Life.</li> <li>High Durability</li> </ul>			
Ordering Information							
Sr	Model Number	Case Lot	Lamp will not Shut down @ high Voltage     Automatic restart after lamp replacement				
31 1	HPY-240-114-IT5-OAF	Description 1x14W T5 <10% THD	50	Automatic restart after lamp replacement			
Fulham extends a limited warranty only to the original purchaser or to the first user for a period of 2 years from the date of manufacture when properly installed and operated under normal conditions of use. For complete terms and conditions, please reference the Fulham product catalog (www.fulham.com) Due to a program of continuous improvement, Fulham reserves the right to make modifications or variations in design or construction to the equipment described. © Fulham Company Limited, All Rights Reserved.						y DOC NUMBER :-FULTDS032 REV :-1.2 Date :-01.04.2013	