

Project: \_\_\_\_\_ Type: \_\_\_\_\_ Model No.: \_\_\_\_\_

Remarks: \_\_\_\_\_

### Description:

The Fulham FHEM14RHxxxx offers both single and double remote lamps for indoor applications. Each lamp head is used as part of an emergency lighting system. The FHEM14RHxxxx has a white thermoplastic housing and incandescent lamp for use in areas requiring remote lighting. Each lamp head is fully adjustable and glare-free.

### FHEM14RHxxxx




FHEM14RH1



FHEM14RH2

### Dimensions:



### Part Number Matrix

**FH**    **EM**    **14**    **RH**    **1**    **6V**    **5**

FireHorse

Emergency Luminaire

Model Number

RH=Remote Head

Number of Heads

Voltage

Wattage Per Head

1 = 1 Head

6V = 6Volts

5 = 5.4W

2 = 2 Heads

12V = 12Volts

7 = 7.2W

9 = 9W

Catalog Model #	# of Heads	Voltage	Total Wattage	Compatible Series
FHEM14RH16V5	1	6 Volts	5.4 Watts	FHEM14650, FHEM1416100*
FHEM14RH26V5	2	6 Volts	10.8 Watts	
FHEM14RH16V9	1	6 Volts	9 Watts	
FHEM14RH26V9	2	6 Volts	18 Watts	
FHEM14RH112V7	1	12 Volts	7.2 Watts	FHEM141250, FHEM1412100*
FHEM14RH212V7	2	12 Volts	14.4 Watts	
FHEM14RH112V12	1	12 Volts	12 Watts	
FHEM14RH212V12	2	12 Volts	24 Watts	

\*Compatible Series are UL Listed with Remote Heads

Fulham Co., Inc extends limited warranty only to the original purchaser or to the first user for the period of **5 years** from the date of manufacture as indicated by the date code stamped on each product and when properly installed and under normal conditions of use, including proper care and charging of batteries. For additional warranty guideline, please refer to our complete product catalog or call customer service at **1-323-599-5000**. DUE TO A PROGRAM OF CONTINUOUS IMPROVEMENT, FULHAM CO., INC RESERVES THE RIGHT TO MAKE ANY VARIATION IN DESIGN OR CONSTRUCTION TO THE EQUIPMENT DESCRIBED.

Address: 12705 S. Van Ness Ave., Hawthorne, CA 90250 Website: www.fulham.com To order this product: Fax: 1-323-754-9060 Email: order@fulham.com 2016-629 Rev A