


SPECIFICATION SHEET : SNS-277-3648-IS

This Is An Original Product From Fulham Co., Inc

Description: Sinehorse Series, High Frequency Electronic, Drop In Replacement for Magnetic, Parallel Wiring, Indoor and Outdoor Sign Applications

This Ballast Will Operate Following Lamps.



Fluorescent Lamp Ballast for any 3,4,5 or 6 lamp combination of 800mA T12HO lamps. NO single lamp may be longer than 8 feet.

ELECTRICAL DATA (277V APPLICATION)

INPUT VOLT: 277V ± 10%, 50/60Hz									
LAMP WATTS/TYPE	F96T12HO	F96T12HO	F96T12HO	F96T12HO	-	-	-	-	-
LAMPS OPERATED	3	4	5	6					
INPUT POWER (W)	248	310	359	412					
LINE CURRENT (A)	0.91	1.13	1.30	1.49					
POWER FACTOR	> 0.9								
THD	< 10 %								
CURRENT CREST FACTOR	< 1.7								
EMI/RFI COMPLIANCE	FCC PART 18-A (Non-Consumer)								
SOUND RATING	" A "								
BALLAST TYPE	INSTANT START								
VOLTAGE TRANSIENTS	-								
INPUT/PROTECTION	FUSE								
OUTPUT/PROTECTION	DEACTIVATED LAMP PROTECTION								
MIN. OPERATING TEMP	-30°C (-22 ° F)								
MAX. CASE TEMP	70 °C (158 ° F)								
APPROVALS/CLASS	UL /cUL LISTED, CLASS " P ", 2 OUTDOOR								

