



LED MODULE BASE NUMBER  
**TM02LN40xx-X02**

**COMPATIBLE DRIVERS**

**Compatible Fulham LED Drivers**

Fulham Part Number	Driver Description	# of Modules/Driver	Wiring Diagram
TCD11200700-9C	700 mA, 9W CC Driver, 120V AC Input, Triac Dimmable	1	A
TC12300700-12L	700 mA, 12W CC Driver, 230V AC Input	1	A
TC11200700-18C	700 mA, 18W CC Driver, 120V AC Input	2	B
T1T11200700-18C	700 mA, 18W CC Driver, 120V AC Input, Triac Dimmable	2	B
T1UNV0700-28C	700 mA, 28W CC Driver, Universal Input	3	B
T1M1UNV0700-28C	700 mA, 28W CC Driver, Universal Input, 0-10V Dimmable	3	B
T1M4UNV0700-100L/C	700 mA, 100W CC Driver, Universal Input, 4 output channels, 0-10V Dimming	16 (4/Ch)	F
T1A4UNV0700-100L/C	700 mA, 100W CC Driver, Universal Input, 4 output channels, DALI, 1 control channel	16 (4/Ch)	F
T2A4UNV0700-100L/C	700 mA, 100W CC Driver, Universal Input, 4 output channels, DALI, 2 control channels	16 (4/Ch)	F
T4N4UNV0700-100K/B	700 mA, 100W CC Driver, Universal Input, 4 output channels, DMX/DALI, 4 control channel	16 (4/Ch)	F
FHS2-UNV-36L	HotSpot2 at 200 - 700 mA output.		

**NOTE:**

1. Subject to rated loading conditions.
2. Modules are polarity sensitive.  
Ensure that "positive" from LED Driver is connected to "positive" of LED modules and that "negative" from LED Driver is connected to "negative" of LED modules.  
Polarities of modules are marked with "+" for positive and "-" for negative.
3. List is subject to change without notice.
4. Reference Fulham's ThoroLED light engine wiring diagrams sheet.

Reference spec sheet of respective driver for warranty information.