


























**Description : WorkHorse Series Versatile, Solid State Electronic Ballast. Small Case Size, High Power Factor, Light Weight, Available In 120/230/277V 50/60 Hz.**

**This Ballast Will Operate Following Lamps.**



T12VHO

**ELECTRICAL DATA ( FOR 230V APPLICATION)**

INPUT VOLT: 230V ± 10%, 50/60Hz							
LAMP WATTS/TYPE	F48T12VHO	F60T12VHO	F72T12VHO	F96T12VHO	-	-	-
LAMPS OPERATED	1						
WIRING DIAGRAM #	19						
INPUT WATTS	114	134	148	200			
LINE CURRENT	0.53	0.62	0.68	0.91			
POWER FACTOR	0.94	0.94	0.94	0.95			
BALLAST FACTOR	0.94	0.93	0.89	0.92			
EFFICACY FACTOR	0.82	0.69	0.60	0.46			
THD	33%	32%	32%	30%			
EMI/RFI COMPLIANCE	FCC PART 18-A (NON-CONSUMER)						
SOUND RATING	" A "						
BALLAST TYPE	INSTANT START						
VOLTAGE TRANSIENTS	ANSI C82.11 - 1993						
INPUT/PROTECTION	FUUSE						
OUTPUT/PROTECTION	-						
MIN. STARTING TEMP	- 18 °C ( 0 ° F )						
MAX. CASE TEMP	70 °C ( 158 ° F )						
TYPE "HL" APPROVAL	APPROVED FOR HAZARDOUS LOCATION						
ENERGY STAR 4.0	-						
APPROVALS/CLASS	UL /cUL LISTED, CLASS " P ", 1 OUTDOOR						

Fulham Co., Inc extends limited warranty only to the original purchaser or to the first user for the period of 5 years from the date of manufacture as indicated by the date code stamped on each product and when properly installed and under normal conditions of use. For additional warranty guide line, please refer to our Complete Product Catalog OR call Customer Service at 1-323-599-5000.

DUE TO A PROGRAM OF CONTINUOUS IMPROVEMENT, FULHAM Co., INC RESERVES THE RIGHT TO MAKE ANY VARIATION IN DESIGN OR CONSTRUCTION TO THE EQUIPMENT DESCRIBED.

Address : 12705 South Van Ness Ave., Hawthorne, CA 90250 Tel.: 1-323-599-5000, Fax.: 1-323-754-9060. Website: [www.fulham.com](http://www.fulham.com) 2006-168-12 rev B